

NYC Approved LED Red Exit - Battery Backup



Long Life, Maintenance Free Ni-Cad Battery

City of New York approved heavy duty emergency exit unit offers high efficiency in an easy to install, durable package.

This self-contained unit with sturdy steel design meets the requirements of all five boroughs of New York City.

Emergency unit is OSHA compliant and contains a long lasting Ni-Cad battery backup for essential illumination during a power outage.

FEATURES

- 120/277V dual voltage operation
- Red EXIT letters - 8" height and 1" stroke
- 20-gauge steel housing with white powder coating
- Ceiling, wall, or side mounting capability (canopy included)
- Test switch and AC supply indicator
- Removeable knockout chevron directional arrows
- Battery backup with accessible test button for 90 minutes of illumination during a power outage
- Suitable for damp locations
- Meets UL924, NFPA 101, NEC, and OSHA standards

APPLICATIONS

- Emergency lighting for office, industrial, retail and other public spaces





Job Name/Title: _____ Catalog Number _____

Contractor: _____ Notes: _____

NYC Approved LED Red Exit - Battery Backup

GENERAL SPECIFICATIONS

Input Voltage: 120/277V (dual voltage)
Frequency: 50/60 Hz
Dimmability: No
Avg. Rated Life: 500 uses
Wet / Damp / Dry Location: Damp
Construction: Steel
Recharge time: 24 hrs
Runtime: >/= 90 minutes
Unit Weight: 6.39 lbs
Battery Backup: 3.6V, 400mA Ni-Cad
Ambient Operating Temperature: 50°F to 104°F



SPECIFICATIONS / ORDER INFO

Catalog Number	Order Code	UPC	Mounting	Dimensions	Pk-Qty
ES/LED/RW/B-NYC	75120	751338031876	Wall, side or ceiling	14.5" x 2.3" x 10.5"	4-PK

NOMENCLATURE

Example: **ES/LED/RW/B-NYC**

ES=Exit Sign / **LED**=LED / **RW**=Red Letters / **B**=Battery Backup / **NYC**=New York City Approved

©2019 Topaz Lighting Corp.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Fixture may not be compatible with all dimmers. Visit www.topaz-usa.com for up-to-date dimmer compatibility information. Specifications subject to change without notice.