



Southwire™

4-11/16" SQUARE TO ROUND FIXTURE RINGS

FEATURES

- Angled slots on the covers compensate for up to 12° of box misalignment on upright framing members
- Not rated for ceiling fan support, static fixture load only
- Fixture Ears 2-3/4" on center

APPLICATIONS

- 4-11/16" square to round raised device rings are used to mount light fixtures in walls and ceilings
- Rings convert a 4-11/16" square box to a 3-1/2" round opening with 8-32 threaded mounting tabs for lighting retrofit applications

STANDARD MATERIAL

- Galvanized steel

CERTIFICATIONS

- UL, cULus Listed



72C3-F



| PART # | DESCRIPTION | RAISED | O.C. FIXTURE EAR | CUBIC INCHES (CM ³) | MASTER QTY. |
|------------|------------------------------------|--------|------------------------|------------------------------------|----------------|
| 72C3-F | 4-11/16" SQUARE TO 3-1/2" ROUND | FLAT | 2-3/4" | --- | 25 |
| 72C3 | | 1/2" | 2-3/4" | 3.5 (57.4) | 25 |
| 72C3-5/8 | | 5/8" | 2-3/4" | 4.8 (78.7) | 25 |
| 72C3-3/4 | | 3/4" | 2-3/4" | 5.4 (88.5) | 25 |
| 72C3-1 | | 1" | 2-3/4" | 6.5 (106.6) | 25 |
| 72C3-1-1/4 | | 1-1/4" | 2-3/4" | 9.5 (155.7) | 25 |
| 72C3-1-1/2 | | 1-1/2" | 2-3/4" | 10.0 (163.9) | 25 |
| 72C3-2 | | 2" | 2-3/4" | 12.9 (211.39) | 25 |

Rev. 1, 3/24

**BUILT FOR DURABILITY.
BUILT FOR RELIABILITY.
BUILT FOR WORK.™**

1-855-798-6657 | SOUTHWIRE.COM

©2024 Southwire Company, LLC. All rights reserved.
*Registered Trademark & ™Trademark of Southwire Company, LLC.



Southwire™

4-11/16" SQUARE TO ROUND FIXTURE RINGS



72C3



72C3-5/8



72C3-3/4



72C3-1



72C3-1-1/4



72C3-1-1/2



72C3-2

Rev. 1, 3/24

**BUILT FOR DURABILITY.
BUILT FOR RELIABILITY.
BUILT FOR WORK.™**

1-855-798-6657 | SOUTHWIRE.COM

©2024 Southwire Company, LLC. All rights reserved.
*Registered Trademark & ™Trademark of Southwire Company, LLC.