

LED LINEAR T8- BALLAST BYPASS EMERGENCY BATTERY BACKUP

SUGGESTED APPLICATIONS

- · Commercial, hospitality
- Office
- Education
- Retail
- Warehouse

FEATURES

- Integrated battery backup provides 90 minutes of illumination during power outage
- Easy access push to test button
- Eliminate the ballast with direct wiring to line voltage
- Single End wiring connection
- Polycarbonate with aluminum heat sink
- Replacement for traditional fluorescent T8 tubes
- ETL Sanitation Listed NSF/ANSI Standard 2 Food Equipment, Splash Zone (Not for Direct Food Zone)
- Available in 4' length, 3500K 6500K CCT



INPUT VOLTAGE: 120-277V

FREQUENCY: 50/60HZ

POWER FACTOR, THD %:

>0.9;<25%

UL TYPE B, BALLAST BYPASS

LAMP EFFICACY: UP TO 127 LPW

CRI: 82

BEAM ANGLE: 140°

LIGHT EMITTING AREA: 240°

LIFETIME (L70): 50,000 HOURS

ENCLOSED FIXTURE RATED

NON SHUNTED LAMP HOLDER REQUIRED

BASE: G13





















LED LINEAR T8- BALLAST BYPASS EMERGENCY BATTERY BACKUP

ITEM SPECIFICATIONS | ORDER INFO

MODEL #	ORDER CODE	UPC	LAMP LUMENS	WATTAGE	EM Lumens	INPUT CURRENT @120V/277V	ССТ	DLC ID
L4T8B-15-35K-PCEM	75774	032886305214	1,850	15W	550	140/60mA	3500K	S-GM5UWJ
L4T8B-15-40K-PCEM	75775	032886305221	1,900	15W	550	140/60mA	4000K	S-4TX0AI
L4T8B-15-50K-PCEM	75776	032886305238	1,900	15W	550	140/60mA	5000K	S-F59WGC
L4T8B-15-65K-PCEM	75777	032886305245	1,900	15W	550	140/60mA	6500K	

NOMENCLATURE

Example: L4T8B-15-xxK-PCEM

PRODUCT	SIZE	SHAPE	UL TYPE	WATTAGE	CCT	OPTIONS
L = LINEAR TUBE	4FT	Т8	BALLAST BYPASS	15W	3500K 4000K 5000K 6500K	PC = POLY CARBONATE EM = EMERGENCY BATTERY BACKUP

ENERGY SAVINGS Based on 12 hours/day and \$0.11/kWh

MODEL #	LED LAMP WATTAGE	FLUORESCENT REPLACEMENT WATTAGE	WATTS SAVED	YEARLY SAVINGS	5 YEAR SAVINGS
L4T8B-15-xxK-PCEM	15W	32W T8	17W	\$11	\$53

DIMENSIONS | WEIGHT

MODEL #	MOL	MOD	WEIGHT
	(IN)	(IN)	(LBS)
L4T8B-15-35K-PCEM	47.24	13	0.88



Breaker 1(Battery charging)

WIRING DIAGRAM



NOTE

DLC Primary Use - Internal Driver/Line Voltage (UL Type B) Lamps

Bypass Type B operation requires non-shunted lamp holders. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. FIVE (5) YEAR LIMITED WARRANTY: SOUTHWIRE COMPANY, LLC: For details visit: https://southwire.com/resources/warranties

Specifications are subject to change without prior notice. Replacement wattage shown depends on application and fixture.



Breaker 2