



Southwire™

4" SQUARE TO ROUND FIXTURE RINGS

SOUTHWIRE "PERFECT FIT DESIGN"

FEATURES

- Dual-direction 8-32 device mounting tabs allow the installer to obtain a perfect fit for signal, lighting and security cameras without having to disassemble canopy fixture
- Not ceiling fan support rated (Static fixture load only)
- Fixture Ears 2-3/4" on center

APPLICATIONS

- 4" square to round raised Perfect Fit rings are mounted in ceiling or wall applications where proper alignment of any device or fixture is needed with canopy installed
- They are typically used on exit signs, emergency lights, ceiling fixtures, security cameras, wall sconce lights and electronic devices

STANDARD MATERIAL

- Galvanized steel

CERTIFICATIONS

- UL, cULus Listed



EXR-F



EXR-2

PART #	DESCRIPTION	RAISED	O.C FIXTURE EARS	CUBIC INCHES (CM³)	MASTER QTY.
EXR-F	4" SQUARE TO 4" ROUND, PERFECT FIT	FLAT	2-3/4"	---	25
EXR-1/2		1/2"		3.3 (54.1)	25
EXR-5/8		5/8"		4.3 (70.5)	25
EXR-3/4		3/4"		5.0 (81.9)	25
EXR-1		1"		6.8 (111.5)	25
EXR-1-1/4		1-1/4"		8.5 (139.3)	25
EXR-1-1/2		1-1/2"		10.3 (168.8)	25
EXR-2		2"		13.5 (221.3)	25

Rev. 1, 3/24

**BUILT FOR DURABILITY.
BUILT FOR RELIABILITY.
BUILT FOR WORK.™**

1-855-798-6657 | SOUTHWIRE.COM

©2024 Southwire Company, LLC. All rights reserved.
*Registered Trademark & ™Trademark of Southwire Company, LLC.